

## Le 275 DE Control



Studied to satisfy the most demanding music lovers, the new 275DE amplifier besides its musicality and its transparency, gives the comfort of 75 watts power output on each channel. That power output is modulated by a pair of KT88 triodes "JJ Electronique" connected according to a completely symmetric diagram in AB class. This disposition gives a high input sensitivity allowing the using of the 220 DE without any external pre amplifier in its "Control" version.

The all components are wired in 2 separated printed circuits for the amplifier and the power supply. The cabinet is composed of 3 steel cases maintained together by screws. Such an arrangement has the result to give an uncommon rigidity to the housing carrying a perfect protection of the electronic.

The originality of the mounting is designed before all for the benefit of the music.

All the parts are oversized, in particular the audio transformers guarantee a bandwidth of more than 60 kHz and they give a total weight of about 20 kg.

The user of a 275 DE amplifier is a lover of technical and musical perfection and concerned at a very high level by an optimal quality / price ratio.

The « Control » model is equipped of 4 line inputs at the rear of the chaise. These inputs can be selected by a selector in front panel. Moreover, a monitoring input/output also selectable in front panel allows the connection of a tape recorder.

|                           |                         |
|---------------------------|-------------------------|
| Power requirement         | 230 Volts               |
| Power consumption         | 500 Watts               |
| Power output              | 2 x 75 Watts à 8 Ohms   |
| Input Sensitivity         | 0,5 V                   |
| Power bandwidth (-3 Db)   | 20 Hz 60 KHz            |
| Total harmonic distortion | 0,4 %                   |
| Vacuum tubes used         | 4 x KT88JJ - 4 x 6SN7GT |

| GENERAL      |  |
|--------------|--|
| Power :      | Three terminals sockets CEE Standard                 |
| Input :      | RCA socket insulated from chaise                     |
| Output :     | Terminal posts for 4 mm banana plug or tripped wire. |
| Dimensions : | 380 (W) x 160 (H) x 300 (D)                          |
| Net Weight : | 20 Kg  |

LABORATOIRE

**J.C. Verdier**

5/7 rue d'Ormesson  
93800 Epinay sur Seine - FRANCE  
Phone : (33) 1 48 41 89 74  
Fax : (33) 1 48 41 69 28  
Web : <http://www.jcverdier.com>  
Email : [jcverdier@jcverdier.com](mailto:jcverdier@jcverdier.com)

**High-End Turntables  
& Vacuum Tubes  
Amplifiers**